

**ROCKY MOUNTAIN POWER**  
**ELECTRIC SERVICE REGULATION NO. 4**  
**STATE OF UTAH**

**Supply and Use of Service**

**1. SUPPLY OF SERVICE**

Unless otherwise specifically provided in the electric service schedule or contract, the Company's rates are based upon the furnishing of electric service to the Customer's premises at a single Point of Delivery and at a single voltage and phase classification.

**(a) Individual Customer**

Each separately operated business activity and each separate building will be considered an individual Customer for billing purposes. If several buildings are occupied and used by one Customer in the operation of a single and integrated business enterprise, the Company may furnish electric service for the entire group of buildings through one service connection at one Point of Delivery. All such buildings shall be on the same premises undivided by a dedicated street, highway or other public thoroughfare or railway.

Should the Customer request service from the Company through more than one Point of Delivery, or request service from the Company at more than one voltage or phase, each service connection will be separately metered and billed. If the size of the load exceeds standard transformer capacity and the Company elects to set more than one transformer of the same voltage and phase, the customer shall be required to provide for, as directed by the Company: 1) a totalized metering scheme wherein the individual metered service are electronically summed into a single meter; or 2) a single point of metering on the primary side of the transformers while maintaining secondary delivery as directed by the Company. The Customer will be responsible for the required meter cabinets, conduits and connections required for primary or totalized metering.

**(b) Reactive Power**

All electric service schedules in this tariff are based upon the Customer minimizing his/her reactive power load.

(continued)

(N)  
|  
(N)

(L)  
to  
p.2